

BIOS UPDATE PROCEDURE: SAPPHIRE PULSE RADEON RX 5600 XT 6G GDDR6 OC

INTRODUCTION:

The BIOS bat files contained in the ZIP file are **ONLY** applicable to the following board part numbers of the PULSE RX 5600 XT 6GB Graphics card (SKU 11296-01-20G)

- 299-4E411-002SA
- 299-5E411-002SA
- 299-4E411-002FC

Executing the bat file with board part numbers other than those listed in this document may cause the system fail to boot. Please check the product labeling to make sure the board part number on your graphics card matches what has been listed before updating the BIOS. To confirm the board part number on the graphics card please check the label located on the reverse of the Graphics Card.



HOW TO UPDATE THE V BIOS

STEP 1:

Save and unzip **PULSE 5600 XT BIOS_update_V1.02** in Windows

STEP 2:

Install the AMD BIOS Flash Utility: **AMDvBFlash_v3.04.exe**

STEP 3:

Turn Off the Computer

STEP 4:

Refreshing the Silent Mode BIOS (135W TGP)

A. Toggle the BIOS Switch to the Left Hand Side as shown below:



- B. Turn on the Computer
- C. In the PULSE 5600 XT **BIOS_update** Folder: Double click **BIOS_update_SW_left.bat**
- D. The CMD window will close after the refresh has completed

STEP 5

Restart the System

STEP 6

Turn off System

STEP 7

Refreshing the **Performance Mode BIOS (160W TGP)**

- A. Toggle the BIOS Switch to the Right Hand Side as shown below:



- B. In the **BIOS_update** Folder: Double Click **BIOS_update_SW_right.bat**
- C. The CMD window will close automatically once the refresh has completed

STEP 7

Restart the System

If during this procedure you need technical support please go to:

<https://support.sapphiretech.com/Default.asp?lang=eng>